

Simple pushbutton adjustment of limit switches



### Tubular motor with pushbutton limit switch

**M size**  
Ø 45 mm

**Even simpler limit switch adjustment using the pushbutton** corresponding to the direction of rotation.

**The built-in circuit board allows a number of motors to be connected and controlled in parallel** from a single point without the need for additional control units.

**Easy to install** thanks to the new compact support and innovative click system to fasten the drive wheel.

Wired and/or radio connection to climatic sensors via external control units.

Code	Description	Pcs./pack	Certificates
<b>E QUICK M 817</b>	Pushbutton limit switch, 8 Nm, 17 rpm, 15 kg*	1	NF CE
<b>E QUICK M 1026</b>	Pushbutton limit switch, 10 Nm, 26 rpm, 18 kg*	1	NF CE
<b>E QUICK M 1517</b>	Pushbutton limit switch, 15 Nm, 17 rpm, 28 kg*	1	NF CE
<b>E QUICK M 3017</b>	Pushbutton limit switch, 30 Nm, 17 rpm, 56 kg*	1	NF CE
<b>E QUICK M 4012</b>	Pushbutton limit switch, 40 Nm, 12 rpm, 75 kg*	1	NF CE
<b>E QUICK M 5012</b>	Pushbutton limit switch, 50 Nm, 12 rpm, 95 kg*	1	NF CE

\*Lifted weight, value calculated with 60 mm diameter octagonal roller

Products also available in multiple packs. For more information, contact your local dealer.

### TECHNICAL SPECIFICATION

Code	E QUICK M 817	E QUICK M 1026	E QUICK M 1517	E QUICK M 3017	E QUICK M 4012	E QUICK M 5012
<b>ELECTRICAL SPECIFICATIONS</b>						
Power supply (Vac/Hz)	230/50					
Current draw (A)	0.55	0.78	0.75	1.10		
Power (W)	120	150	170	250	245	250
Power consumption in stand-by (W)	<0.5					
<b>PERFORMANCE</b>						
Torque (Nm)	8	10	15	30	40	50
Speed (rpm)	17	26	17	17	12	12
Lifted weight* (kg)	15	18	28	56	75	95
Number of turns before the stop	92					
Continuous operating time (min)	4					

### DIMENSIONAL DATA

Length (L) (mm)	426	451	486
Weight of motor (kg)	2.15	1.95	2.45
Pack dimensions (mm)	90x90x465	90x90x500	90x90x530

Protection class IP44.

\*Value calculated with 60 mm diameter octagonal roller.

### POWER CABLE

Cable length 2.5 m, 4 wires in cable



### DIMENSIONS

